

Series Features

· Solid State Charger






277VAC 60 Hz 4.0 Watt

For Use on Single or Double Lamps


• Illuminates Rapid Start, Instant Start, High Output, Slim Line, Circline, U-Shaped or Compact Lamps



· Maintenance-Free

Converts Fluorescent Fixtures to Emergency Lighting

- Provides 1.5-Hour Illumination for Single or Double Lamps
- Completely Self-Contained Inside or Above Lighting Fixture
- · Compact Steel Housing
- · Convenient Length Lead Wires



- Red (Power On) Indicator
- · Operating Range: 50°-140°F
- · Warranty: 2-5 Years
- UL Listed

Linear Lamps

Lamps Operated	Qty.	EFB40 500 Lumens	700	EFB40-2 1300 Lumens	650	650	650
2:-4: Rapid, Instant Energy Saving, T8 and T12	1	Х	Х	Х			
2:–4: Rapid, Instant Energy Saving, T8 and T12, HO & VHC	2		X**	X**			
5:–8: Rapid, Instant Energy Saving, T8 and T12, HO & VHC) 1		Χ	Χ			
20W-40W Circline	1	Х	Х	Х			
20W-40W Circline	2		Х	Χ			

Compact Lamps

Lamps Operated	Qty.	EFB40 500 Lumens	EFB80 700 Lumens	EFB40-2 1300 Lumens	650	EPLB26 650 Lumens	650
5-, 7-, 9- & 13-Watt Twin Tube (2 pin)	1				Х		
9W-13W USA Quad Tube (2 pin)	1				Х		
18W-26W Quad Tube (2 pin)*	1					X	
10W-26W Quad Tube (4 pin)	1 or 2						X
18W–39W Long Compact	1						X
40-Watt Biax	1		Х	Х			
50-Watt Biax	1			Х			
55-Watt Biax	1			X			
18W-26W Triple Tube (4 pin)	1 or 2						X
32W-42W Triple Tube (4 pin)	1						Х

^{*22- &}amp; 28-Watt 15 mm lamps are not compatible.

Ordering Information

EFB40	-TMK
Model	Options



An affordable alternative to conventional emergency lighting, the EFB Series is a fluorescent ballast, which enhances existing AC fixtures by illuminating 1 or 2 lamps during a power failure.

Dimensions

EFB40-2

Height: 1.5" Length: 13.125" Width: 2.375" Mtg. Ctr.: 12.75"

ALL OTHERS

Height: 1.5" Length: 9.5" Width: 2.375" Mtg. Ctr.: 9.0"

Options Add Suffix to Catalog Number

-FC Flex Cord

-RTSK Remote Test Switch Kit (EFB Series)

-TMK Top Mount Kit



^{**}Note: Two-lamp emergency is not possible with all electronic ballasts. Consult customer service for specific ballast compatibility.