LIFELIGHT 3

LIFELIGHT 3 Series	Power Rating	UPS Cabinet Dimensions			Battery Cabinet Dimensions				Weight (combined)	British Thermal Unit	Battery Type	Voltage (VAC)		Output Protection	Safety Approvals
	KVA/KW	W	H	D	No.	W	H	D	(lbs)	BTU's		Input	Output		
	3	42"	71"	22.5"	not required				980	816	Sealed, Maintance free (AGM) lead calcium	*Select* 208Y/120VAC, 480Y/277VAC, 208 or 480VAC (Consult factory for others)		Input and output circuit breakers standard	UL924 UL1778 NFPA 101 NFPA 70 NEC
	4.5	42"	71"	22.5"	not required				1100	1224					
	6	42"	71"	22.5"	not required				1350	1632					
	8	42"	71"	22.5"	1	42"	71"	22.5"	1700	2176					
	10	42"	71"	22.5"	1	42"	71"	22.5"	2250	2720					
	12	42"	71"	22.5"	1	42"	71"	22.5"	2700	3264					
	16	42"	71"	22.5"	1	42"	71"	22.5"	2950	4352					
	20	42"	71"	22.5"	1	42"	71"	22.5"	3800	5440					
	24	42"	71"	22.5"	2	42"	71"	22.5"	4350	6528					
	30	42"	71"	22.5"	2	42"	71"	22.5"	5150	8160					
	40	42"	71"	22.5"	3	42"	71"	22.5"	6790	10880					
	50	42"	71"	22.5"	4	42"	71"	22.5"	8384	13600					
	60	50"	71"	32"	Consult Factory					16320					
	80	50"	71"	32"	Consult Factory					21760					
	100	50"	71"	32"	Consult Factory					27200					
	125	50"	71"	32"	Consult Factory					34000					

The Lifelight 3 provides the simplicity and reliability that is critical when providing an alternative source of power to any environment. Easy installation ... "simplicity" ... connect the 3 to the emergency circuit(s) and everythingis backed up... "reliability"...during a power outage. All lighting connected to the 3 will simply continue to operate at "full light output". Watchdog Software keeps you environment safe while self-diagnostics help maintain equipment to a high standard. Superior surge suppression assures the highest quality of power being delivered to all loads, all the time. Equipment and lamp life are maximized.

ORDERING INFORMATION

Choose the bold face catalog nomenclature that best suites your needs.

Write them on the appropriate line. Order accessories as separate catalog number.

Example:

OE3 - 12.0 - 208Y/120 208Y/120- EMB OCB/120/3/20/1

Description of example:

(12.0 KW, 208Y/120 Voltage In, 208Y/120 Voltage Out, External Maintenance Bypass Switch, 3 Output 120 Voltage Circuit Breakers at 20amps, 2 pole)

OE3 — — — —

FAMILY

POWER RATING

KW

3.0
4.5
6.0
8.0
10.0
12.0
16.0
20.0
24.0
30.0
40.0
50.0
60.0
80.0
100.0
125.0

VOLTAGE [1]

Input - Output

208Y/120 - 208Y/120
208Y/120 - 480Y/277
480Y/277 - 208Y/120
480Y/277 - 480Y/277
208 - 208Y/120
208 - 480Y/277
480 - 208Y/120
480 - 480Y/277

OPTIONS

ECM120 - 120V Environmental control module[2]/qty
ECM277 - 277V Environmental control module[2]/qty
NOF - Normally OFF output circuit/voltage/qty/pole
NOH - Normally OFF "Hold ON"/voltage/qty/pole
OCB - Output circuit breakers/voltage/quantity/amps/pole
EPO - Emergency power off
RSSP - Remote Indicator Panel
SNMP - SNMP Card
FC - Form C Contacts
SRB - Seismic rated bracket
STU3 - Onsite start-up
IDB - Internal dimmer bypass
EMB - External maintenance bypass switch
EW - Extended warranty

TIME [3]

Minutes

5
10
15
20
25
30
45
60
90 (Standard)
120
180
240

NOTES:

1-Consult factory for other voltage requirements. Special voltages may effect the weight, size and number or cabinets.
2-One ECM is used per switching device or circuit.
3-Consult factory for other run times.

Specifications subject to change without notice.

Big Beam Emergency Systems, Inc
290 East Prairie St. Cystal Lake, IL 60014
815-459-6143 - www.siltron.com