

The BBT offers a fast and easy solution to your Emergency Lighting needs. If you are looking to back up your fixtures in the event of a power outage, the BBT is the most economical choice. The BBT offers an easy installation, with double-ended power. Provides 427lm/s during a power outage with a minimum runtime of 90 minutes.

#### FEATURES

- 100/277 voltage
- 2' 9W or 4' 18W
- 120lm/w
- 4000K & 5000K Available
- White caps
- Aluminum Heat Sync and Plastic Lens
- LED Charge Rate Indicator
- Test Switch
- Damp Location Suitable
- LED
- 50,000hrs L70
- ETL Listed

#### WARRANTY

5 Year Warranty



### BBT

The BBT is unique in the sense where it comes with fully integrated Emergency Battery Backup



- Test Button
- Main Power
- Charge
- Malfunction
- Sensor

**Test button:** Press the test button to check the emergency function. When connected with AC power for 8 seconds, press this button, lamp will be in emergency status.

**Green lamp on:** AC power(AC 100-277V)connected.

**Red lamp on:** Battery is charging. It will turn off when batteries are full charged.

**Yellow lamp on:** Tube is on malfunctioned. (Please call retailer when yellow light turns on).

**Blue lamp on:** Sensor is working.



Series	Wattage	Kelvin Temp
BBT	9 = 9W (2')	4 = 4000K
	18 = 18W (4')	5 = 5000K