

Hazardous Area Products

HE



Dimensions

HE	
Height:	12.0"
Width:	15.0"
Depth:	8.8"

The HE Series is designed for use in Class I, Division I hazardous areas. Lighting fixtures and exit fixtures are available for mounting directly to the housing or can be remotely mounted.

Ordering Information

HE	12	N	14
Series	DC Battery Voltage	Battery Type	Battery Amp/Hour



Made in USA

Series Features

	<p>NEC ENVIRONMENT RATINGS</p> <ul style="list-style-type: none"> • Meets or Exceeds UL Specifications for Use in the Following Areas: Class I, Division I, Groups C & D Class II, Division I, II Groups E, F & G Class III
	<ul style="list-style-type: none"> • Integrated Solid State System • Controlled, Automatic Charger • Dual-Voltage Transformer for 120/277 VAC Operation
	<ul style="list-style-type: none"> • Bi-Pin Halogen
	<ul style="list-style-type: none"> • Sealed Nickel Cadmium Battery (N) • 6- or 12-Volt Operation • Maintenance-Free
	<ul style="list-style-type: none"> • Completely Self-Contained Operation • Heavy Cast, Copper-Free Aluminum Housing • Sealed Test Switch • Power On Indicator • Pre-Drilled Hole for AC Power • UL-Listed Enclosures and Fixtures

Unit Information

Model Number	Watts per Hour							
	1.5	2	3	4	5	6	7	8
HE6N7	18	14	9	7	-	-	-	-
HE6N14	36	28	18	14	11	9	8	7
HE6N21	54	42	27	21	17	13	11	10
HE6N28	72	56	36	28	23	18	16	14
HE12N7	36	28	18	14	11	9	8	7
HE12N14	72	56	36	28	23	18	16	14

For remote fixture applications, use one of the above power units and remote fixtures/exits found on page 62. Remote fixtures/exits must be the same DC voltage and total remote wattage must not exceed the 1.5-hour capacity of the above power unit. 12-volt equipment is suggested for longer wire runs.

6-Volt Hazardous Area Emergency Lighting Power Units (Complete with Batteries and Chargers)



HE6N7-1EP-H10

- Single-head unit with 10-watt halogen lamp



HE6N14-1EP-H20

- Single-head unit with 20-watt halogen lamp

HE6N7-1XP1R-H10*

- Single exit fixture with 10-watt halogen lamp

HE6N14-1XP1R-H20*

- Single exit fixture with 20-watt halogen lamp



HE6N14-2EP-H10

- Double-head unit with 10-watt halogen lamps



HE6N14-1EP-1XP1R-H10*

- Single-head & single exit with 10-watt halogen lamps

HE6N21-2EP-H20

- Double-head unit with 20-watt halogen lamps

HE6N21-1EP-1XP1R-H20*

- Single-head & single exit with 20-watt halogen lamps

For power units with lighting heads and/or exit fixtures mounted directly to the housing, choose from the models listed above. These units are supplied with a swivel elbow for each lighting fixture. Conduit is to be supplied by the installer.

*Exit signs are lit in DC power only.