

Series Features

NEC ENVIRONMENT RATINGS

- Meets or Exceeds UL Specifications for Use in the Following Areas: Class I, Division I, II Groups C & D
Class II, Division I, II Groups E, F & G
Class III



- Integrated Solid State System
- Controlled, Automatic Charger
- Dual-Voltage Transformer for 120/277 VAC Operation



- LED



- Sealed Nickel Cadmium Battery (N)
- 6- or 12-Volt Operation
- Maintenance-Free



- Completely Self-Contained Operation
- Heavy Cast, Copper-Free Aluminum Housing
- Sealed Test Switch
- Power On Indicator
- Pre-Drilled Hole for AC Power
- UL-Listed Enclosures and Fixtures

HE



The HE Series is designed for use in Class I, Division I hazardous areas. Lighting fixtures and exit fixtures are available for mounting directly to the housing or can be remotely mounted.

Dimensions

HE
Height: 12.0"
Width: 15.0"
Depth: 8.8"

Unit Information

Model Number	Watts per Hour							
	1.5	2	3	4	5	6	7	8
HE6N7	18	14	9	7	-	-	-	-
HE6N14	36	28	18	14	11	9	8	7
HE6N21	54	42	27	21	17	13	11	10
HE6N28	72	56	36	28	23	18	16	14
HE12N7	36	28	18	14	11	9	8	7
HE12N14	72	56	36	28	23	18	16	14

For remote fixture applications, use one of the above power units and remote fixtures/exits found on page 62. Remote fixtures/exits must be the same DC voltage and total remote wattage must not exceed the 1.5-hour capacity of the above power unit. 12-volt equipment is suggested for longer wire runs.

Ordering Information

HE Series	12 DC Battery Voltage (6 - 6-Volt) (12 - 12-Volt)	N Battery Type (N - NiCad)	14 Battery Amp/Hour	-1EP-1XP1R-LED Options (EP-Light Head) (XP-Exit)



Made in USA

6-Volt Hazardous Area Emergency Lighting Power Units (Complete with Batteries and Chargers)



HE6N7-1EP-LED

- Single-head unit with 3-watt LED lamp



HE6N14-1EP-LED

- Single-head unit with 3-watt LED lamp

HE6N7-1XP1R-LED

- Single exit fixture with 3-watt LED lamp

HE6N14-1XP1R-LED*

- Single exit fixture with 3-watt LED lamp



HE6N14-2EP-LED

- Double-head unit with 3-watt LED lamps



HE6N21-2EP-LED

- Double-head unit with 3-watt LED lamp

HE6N14-1EP-1XP1R-LED

- Single-head & single exit with 3-watt LED lamp

HE6N21-1EP-1XP1R-LED

- Single-head & single exit with 3-watt LED lamp

For power units with lighting heads and/or exit fixtures mounted directly to the housing, choose from the models listed above. These units are supplied with a swivel elbow for each lighting fixture. Conduit is to be supplied by the installer.