Steel Remote Heads

53/55/65



53, H53 & 65 SERIES

53DH, H53DH & 65DH SERIES

Double 5" PAR-36 housings and round mounting plate with powdercoat finish. Fully assembled with swivel and lead wires. Mounts to 4"

Single 5" PAR-36 housing and single gang mounting plate with powder-coat finish. Fully assembled with swivel and lead wires.

Unit Information

	Steel with Beige Finish					
	Lamp Volts	Lamp Watts	Single Head with Mounting Plate	Double Head with Mounting Plate		
Incandescent PAR-36 Sealed Beam	6	8	53F6B-8	53DHF6B-8		
	6	18	53F6B-18	53DHF6B-18		
	6	25	53F6B-25	53DHF6B-25		
	12	18	53F12B-18	53DHF12B-18		
	12	25	53F12B-25	53DHF12B-25		
	12	30*	53S12B-30	53DHS12B-30		
Halogen PAR-36 Sealed Beam	6	6	H53F6B-6	H53DHF6B-6		
	6	8	H53F6B-8	H53DHF6B-8		
	6	12	H53F6B-12	H53DHF6B-12		
	6	20	H53F6B-20	H53DHF6B-20		
	12	8	H53F12B-8	H53DHF12B-8		
	12	12	H53F12B-12	H53DHF12B-12		
High-Intensity Tungsten Wedge Base	6	6	65F6B-6	65DHF6B-6		
	6	7.2	65F6B-7	65DHF6B-7		
	6	9	65F6B-9	65DHF6B-9		
	12	7	65F12B-7	65DHF12B-7		
	12	9	65F12B-9	65DHF12B-9		
	12	12	65F12B-12	65DHF12B-12		
	12	18	65F12B-18	65DHF12B-18		
	24	7	65F24B-7	65DHF24B-7		
Steel with Cocoa Finish †						
Incandescent PAR-46 Sealed Beam	6	21	55F6C-21	55DHF6C-21		
	6	25	55F6C-25	55DHF6C-25		
	6	30*	55S6C-30	55DHS6C-30		
	12	30*	55S12C-30	55DHS12C-30		
	12	35	55F12C-35	55DHF12C-35		

Unit Information

	Lamp Volts	Lamp Watts		
PAR-46 LED Sealed Beam	12	3.8	LED	
	55 Series Only			

†Each model number designates the color or finish of the head housing and mounting plate:

53F6<u>B</u>-8 = Beige Finish 55F6<u>C</u>-21 = Cocoa Finish

To specify a different color or finish, change the designator letter(s):

B = Beige

- **C** = Cocoa
- GY = Grey

PM = Painted Matte Chrome W = White

53F6GY-8 = Grey Finish

55F6PM-21 = Painted Matte Chrome Finish







55DH SERIES

Double 6" PAR-46 housings and round mounting plate with powdercoat finish. Fully assembled with swivel and lead wires. Mounts to 4" junction box.