

The steel made 53 series remote heads, are a robust option. Operates with Emergency Lights and Exit Systems with Remote Capacity.

FEATURES

- Available in 6V or 12V
- 5W LED Sealed Beam PAR36
- Single Head & Double Head Assemblies
- Chicago Code Compliant



DESCRIPTIONS:

PAR 36 LED SEALED BEAM WITH 72 LEDS.
 FORWARD CURRENT: 25 mA
 PEAK FORWARD CURRENT: 50 mA
 NORMAL OPERATING TEMPERATURE: -40°F TO 105°F
 NORMAL STORAGE TEMPERATURE: -40°F TO 150°F
 ELECTROSTATIC DISCHARGE: 500 VOLT
 SOLDERING TEMPERATURE: 260 (+)-5 °F
 FORWARD VOLTAGE: 3.2 VOLT (2.8 MIN TO 3.6 MAX)
 LUMINOUS INTENSITY: 13000 mcd
 BRIGHTNESS: 400 PLUS LUMENS
 INPUT VOLTAGE: DC 5.1V - 35V



BIG BEAM EMERGENCY SYSTEMS, INC.

CRYSTAL LAKE, IL 60014

INFORMATION CONTAINED HEREIN IS PROPRIETARY INFORMATION OF BIG BEAM EMERGENCY SYSTEMS, INC. THE DISSEMINATION, USE OR DUPLICATION OF THIS INFORMATION FOR ANY PURPOSE OTHER THAN THAT FOR WHICH THE INFORMATION IS PROVIDED IS PROHIBITED BY BIG BEAM EMERGENCY SYSTEMS, INC. EXCEPT BY EXPRESS PERMISSION.

STEEL PAR36 REMOTE HEADS

VOLTAGE	WATTS	SINGLE	DOUBLE	LAMP TYPE
6	5W	LS53F6W	LS53DHF6W	LED
12	5W	LS53F12W	LS53DHF12W	LED