Commercial Emergency Lights

MO



Dimensions

MO

Height: 15.4" Width: 11.7" Depth:

Options Add Suffix to Catalog Number

-BG Beige Finish -BLK Black Finish Cord & Plug for -P2 120VAC Input

Voltmeter* White Finish -W Special Lamp

Wattage (See page 63)

*In Place of Ammeter

Shown in White Finish

The MQ Series combines state-of-the-art unit performance with traditional wall-mount styling. Standard equipment includes Quik-Chek™, our exclusive remote testing feature for emergency lights.











Series Features

OUIK-CHEK™ REMOTE CONTROL TESTING*



- · Verifies Operation of Lamps, Charger and Battery
- Hand-Held Transmitter 1'-50' Range
- Field Adjustable Time Delay 1–90 Minutes
- U.S. Patent #5148158, Canadian Patent #1320246
- Integrated Solid State System
- Multi-Rate, Controlled, Automatic Charger
- Fused AC Input & DC Output Circuit Protection
- Lock Out (Automatic Battery Connect)



- Low-Voltage Battery Cutoff
- Brownout Sensitivity
- Dual-Voltage Transformer for 120/277 VAC Operation
- · Maximum Input Rating


120VAC 60 Hz 0.35 Amps 277VAC 60 Hz 0.15 Amps



- HIT Lamps
- STD Lamp: See Unit Information
- PAR-36 Sealed Beams
- Opt. PAR-36LED Sealed Beams 5W



- Sealed Lead Calcium Battery
- 6-Volt Operation · Maintenance-Free
- Traditional Styling
- 20-Gauge Steel Housing
- Designer Off-White Powder-Coat Finish



- Red (Power On) LED Indicator
- Test Switch
- Ammeter
- UL Listed
- New York City Approved/Calendar #38236

Unit Information

Model Number	Std. Lamp Watt	Watts per Hour								Replacement	
		1.5	2	3	4	5	6	7	8	Battery	
2MQ6S10†	8	32	24	16	12	10	8	7	6	(1) S610SL	
H2MQ6S10†	7	32	24	16	12	10	8	7	6	(1) S610SL	
H2MQ6S16†	12	36	27	18	14	11	9	8	7	(2) S68	
†Chicago Code Approved											

Illumination is rated to 87.5% of nominal system voltage and recharge to full capacity within 48 hours. NEC requires 1.5 hours of emergency illumination.

Ordering Information

LS	2	MQ	6	S	10	-V
LS-LED H-Halogen	Lamp Heads on Unit (0, 1, 2, 3)	Series	DC Battery Voltage	Battery Type (S – Sealed)	Battery Amp/Hour	Options

^{*}See pages 69-70 for additional Quik-Chek™ information.